













































**Sigma CP**  
**Conventional**  
**Fire Control Panel**  
**Quick Reference**  
**Guide**

How To	Do This	Display	Comments
Silence buzzer	<p><b>Alarm/Fault Buzzer Silenced</b></p>  <p>Press button</p>	 Alarm/Fault Buzzer Silenced	Buzzer will resound on next event.
Test lamps	<p><b>Lamp Test</b></p>  <p>Press button</p>	<p>8.8.</p> <p>All lamps on</p>	Buzzer sounds whilst button is pressed
Enable buttons	<p><b>Enable Control</b></p>  <p>Turn key</p>	<p>6 1</p>	Buzzer beeps twice every few seconds
Silence alarms	<p><b>Silence/Sound Alarm</b></p>  <p>Press button</p>	 Alarm/Fault Buzzer Silenced	
Sound alarms	<p><b>Silence/Sound Alarm</b></p>  <p>Press button</p>	 Fire	Buzzer pulses rapidly
Reset	<p><b>Reset</b></p>  <p>Press button</p>		Ensure source of fire event is cleared before resetting.
Disable a zone Step 1	<p><b>Mode</b></p>  <p>Press button until d1 is displayed</p>	<p>d 1</p> <p>First display</p>	
Disable a zone Step 2	<p><b>Select</b></p>  <p>Press button to scroll zones</p>	<p>d5</p> <p>Zone 5</p>	Zone 5 for example
Disable a zone Step 3	<p><b>Enter</b></p>  <p>Press button</p>	<p>Fire in Zone</p> <p>5 6 7</p> <p>Zone Fault</p> <p>Zone 5 fault LED is lit</p>	 General Disablement  <p>d5.</p> <p>Dot flashes to indicate disablement</p>

How To	Do This	Display	Comments
Put a zone into test mode. Step 1	<b>Mode</b>  Press button until t1 is displayed	 First display	
Put a zone into test mode. Step 2	<b>Select</b>  Press button to scroll zones	 Zone 5	Zone 5 for example
Put a zone into test mode. Step 3	<b>Enter</b>  Press button	 Zone 5 fault LED is lit	 Dot flashes to indicate test mode.
Enable a zone Step 1	<b>Mode</b>  Press button until d1 is displayed	 First display	
Enable a zone Step 2	<b>Select</b>  Press button to scroll zones	 Zone 5	
Enable a zone Step 3	<b>Enter</b>  Press button	 Zone 5 LED extinguishes	 General Disablement indicator extinguishes
Disable sounders Step 1	<b>Mode</b>  Press button until db is displayed		
Disable sounders Step 2	<b>Enter</b>  Press button		Dot flashes to indicate bells/sounders are disabled. General disablement and sounder Fault/Disablement indicators lit.

How To	Do This	Display	Comments
Enable sounders Step 1	<p data-bbox="356 153 415 172"><b>Mode</b></p>  <p data-bbox="292 244 477 288">Press button until db is displayed</p>		
Enable sounders Step 2	<p data-bbox="356 296 415 316"><b>Enter</b></p>  <p data-bbox="333 387 440 406">Press button</p>		Dot extinguishes to indicate bells/sounders are enabled. General disablement and sounder Fault/Disablement indicators extinguish.
Activate zone input delays Step 1	<p data-bbox="356 419 415 438"><b>Mode</b></p>  <p data-bbox="292 510 477 555">Press button until Ad is displayed</p>		
Activate zone input delays Step 2	<p data-bbox="356 563 415 582"><b>Enter</b></p>  <p data-bbox="333 654 440 673">Press button</p>		Dot flashes to indicate that delays are active if they have been set in engineering mode. (refer to operation and maintenance manual)
Deactivate zone input delays Step 2	<p data-bbox="356 686 415 705"><b>Mode</b></p>  <p data-bbox="292 777 477 821">Press button until Ad is displayed</p>		Dot flashes to indicate that delays are active if they have been set in engineering mode. (refer to operation and maintenance manual)
Activate zone input delays Step 1	<p data-bbox="356 829 415 849"><b>Enter</b></p>  <p data-bbox="333 920 440 940">Press button</p>		Dot stops flashing to indicate delays have been deactivated
Return system to normal	<p data-bbox="305 952 465 971"><b>Enable Control</b></p>  <p data-bbox="348 1083 421 1102">Turn key</p>		Leaves only Alarm/Fault Warning Silence and Lamp Test buttons operable
For service contract:		Telephone:	

## Notes to Technicians and Testers.

This incite Sigma and Syncro range of panels have been designed to meet AS7240.2 and AS7240.4

These standards are very different in both their panel operation and operating parameters from the old Australian standards, AS4428.1 and AS1603.4.

The main differences are outlined here as follows;

**Access Levels:** AS7240 allows for 4 different access levels as follows:

1. Public Access Level: This level is always active
  - a. Silence the panel buzzer
  - b. Perform a lamp test
  
2. Operator Access Level: This level is entered by turning a key or by entering a code. This is the level accessible to the Fire Brigade.
  - a. All the above plus
  - b. Sound Alarm Devices, e.g. Activate and Evacuation signal
  - c. Silence Alarm Devices
  - d. Reset the panel
  - e. Activate Delays
  - f. Set Test mode
  - g. Disable circuits
  
3. Technician Access Level: This level is entered by entering a code which is different from that used for Access Level 2, or setting a switch which is not normally available to an Operator, e.g behind a locked door.
  - a. All of the above plus
  - b. Changes to the configuration, e.g set delay times, add devices/modules to the panel.
  
4. Engineering Access Level: This level is entered via a laptop or other device using specialised software to upgrade or change the firmware within the panel. This level is only available to the manufacturer and authorised technicians

**Disablement:** This is not an isolate! An isolate allowed the circuit to be monitored and indicate its condition without causing activation. A disablement, depending on the design, may or may not allow a circuit to be powered but will not indicate the state of the circuit. The circuit is disabled.

**Care must be taken when enabling a disabled circuit to ensure that it is not active.  
It is good practice to perform a reset on any disabled detection circuit before enabling it.**

The standard list a disablement as: "Disablements shall inhibit all corresponding mandatory indications or outputs or both, but shall not prevent other mandatory indications and/or outputs."

**Alarm and Fault Test:** Under AS7240, neither alarm test or fault test exists. During maintenance, an installation is required to be tested by activating a detector on that circuit and ensuring that the panel and outputs operate successfully due to that activation. In this way, the integrity of the entire system is ensured.

**Test:** This is similar to a Walk Test, where the detector will activate and then reset approximately 5 seconds later, but the outputs will activate indicating that the entire system is working. Any outputs which must be maintained during a test, such as computer shutdown, will need to be disabled prior to performing any test.

**Power Supplies:** Under AS7240, the power supply must be capable of powering the panel, ALL alarm loads AND charge the batteries. In other words, the panel must be able to operate in all modes without any batteries connected.

**Alarm Delays:** AS7240 allows for alarm delays on sounders and outputs. The majority of panels in Australia will not use this function, but they are included here for completeness. These are configured at Access Level 3, but activated at Access Level 2. Delays under AS7240 can be up to 10 minutes in length.

When the delay is activated and an alarm occurs, the output will not operate until this delay period has expired.

Refer to the Sigma CP Operation and Maintenance Manual, Table 8 for configuration options.

**Earth Fault:** An AS7240 panel will detect if there is an earth fault on the system

**Alarm Verification:** AS7240 does not have alarm verification

**Sounders, Bells and Warning System:** AS7240 does not discriminate between sounders, bells and a warning system. They are all sounders. Controls are provided to silence and re-sound sounders at access level 2.

**Fire Fighters Facility:** AS7240 does not have a Fire Fighters Facility.



## **Sydney**

Block Y, Unit 1, 391 Park Road, REGENTS PARK NSW 2143  
Mail: PO Box 508 GYMEA NSW 2227  
Phone: 1300 INCITE (1300 462 483) | 02 9644 7144  
Fax: 02 9644 7255  
Email: [sales@incitefire.com.au](mailto:sales@incitefire.com.au)  
Technical support: [support@incitefire.com.au](mailto:support@incitefire.com.au)

## **Melbourne**

Address: Unit 120, 45 Gilby Road, MT WAVERLEY VIC 3149  
Phone: 03 9544 2211  
Fax: 03 9544 2212  
Email: [salesvic@incitefire.com.au](mailto:salesvic@incitefire.com.au)

## **Brisbane**

Address: 25 Jeays Street, BOWEN HILLS QLD 4006  
Phone: 07 3252 5366  
Fax: 07 3252 4099  
Email: [salesqld@incitefire.com.au](mailto:salesqld@incitefire.com.au)

## **Perth**

Address: Unit 2, 48 Irvine Drive, MALAGA WA 6090  
Phone: 08 9349 2972  
Email: [saleswa@incitefire.com.au](mailto:saleswa@incitefire.com.au)