
STI ReSet Call Points





incite fire

Denotes a ReSet call point that will interface with most conventional ¹ fire alarm systems. It is ² fitted with two internal ³ resistors 470 (R1) and 680 (R2) ohms. These are easily accessed through the installer terminals as illustrated.

PRODUCT OVERVIEW

The ReSet Call Points are a unique call point that mimic the feel of breaking glass whilst offering the user the benefits and environmental advantages of a re-settable operating element. They are compatible with most conventional fire alarm systems. They are safe to use in areas where glass cannot be used such as food processing plants and leisure centres. As the units can be simply reset they provide an ideal solution for areas that suffer from a high number of false activations such as schools, shopping centres and other public places.

HOW IT WORKS

The 'ReSet' uses a simple yet ingenious patented mechanism which consists of a rigid plastic operating element and an over centre spring mechanism. This arrangement provides real action on operation and simulates break glass activation. An activation indicator drops into view at the top of the window after the 'ReSet' has been operated. The unit is then simply reset with a key and is ready for reuse straight away.

Step 3:

call point.

To reset a simple

key is inserted into

the bottom of the



Step 1: Positive action mimics the feel of breaking glass.



Step 2: A warning indicator drops into view when the call point is activated.



Step 4: A quick turn of the key and the call point is reset and ready for use again straight away.

and environmental advantages of a resettable operating element. · Three year guarantee against

KEY FEATURES General Information · Unique manual call point that

breakage of polycarbonate in normal use (one year guarantee on electromechanical and electronic components).

mimics the feel of breaking glass whilst offering the user the benefits

Design

- An indicator drops into view at the top of the window on activation.
 The unit is then simply reset with a key and is ready for re-use straight away.
- · Waterproof models available, tested to IP67.

Construction

 Extremely attractive, high value look and feel: glass appearance maintains operator deterrence, whilst a visible warning flag confirms activation.

Installation

- Easy installation due to no glass elements that could be broken or incorrectly fitted.
- Surface mounted, 20mm conduit entry points are provided for ease of installation.
- Operating temperature -20°C (-4°F) to 65°C (149°F).

Options

- · Low profile, heavy-duty
- terminations.
- Optional integral cover can be fitted to prevent accidental
- activation.
- Complete functional test with every activation.
- Alternative single pole changeover & double pole versions are also available (Series 02, Series 11).

Accessories:

STI RP-K Reset Key

DIMENSIONS

	Height (mm)	Width (mm)	Depth (mm)
RP Flush	87	87	23
RP Surface	87	87	58